

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (previously presented): An apparatus for use in performing a floating point multiply-accumulate operation, comprising:
 - a plurality of latches that contain a plurality of exponents of operands for the operation;
 - a carry-save adder, coupled to the latches, that receives the exponents of operands and performs a carry-save add operation on the exponents of operands to produce a first result;
 - a control circuit for generating a control signal; and
 - a logic block, coupled to the carry-save adder, that receives the first result and performs a carry-lookahead add operation on the first result to produce a second result, the logic block having a logic circuit that performs an exclusive-OR logic operation between a most significant bit of the second result and the control signal to produce a value for use in the floating point multiply-accumulate operation.
2. (previously presented): The apparatus of claim 1, wherein the logic circuit includes a logic stage for processing said most significant bit in the logic block.
3. (original): The apparatus of claim 2, wherein the redundant logic stage performs the logic operation on the most significant bit in parallel with at least a portion of the carry-lookahead add operation.
4. (original): The apparatus of claim 1, wherein the logic circuit performs the logic operation to produce a shift value for use in the floating point multiply-accumulate operation.
5. (cancelled).
6. (previously presented): An apparatus for use in performing a floating point multiply-accumulate operation, comprising:

a plurality of latches that contain a plurality of exponents of operands for the operation;

a carry-save adder, coupled to the latches, that receives the exponents of operands and performs a carry-save add operation on the exponents of operands to produce a first result;

a control circuit for generating a control signal based upon a Single Instruction Multiple Data operation; and

a logic block, coupled to the carry-save adder, that receives the first result and performs a carry-lookahead add operation on the first result to produce a second result, the logic block having a logic circuit that performs an exclusive-OR logic operation between a most significant bit of the second result and the control signal to produce a value for use in the floating point multiply-accumulate operation.

7. (previously presented): The apparatus of claim 1, wherein the control signal is a pair of complementary signals and wherein the control circuit generates the pair of complementary signals.

8. (original): The apparatus of claim 1, wherein the logic block includes a carry-lookahead adder having complementary logic circuits for providing complementary outputs as the second result.

9-16. (cancelled):

17. (previously presented): An apparatus for use in performing a floating point multiply-accumulate operation, comprising:

a plurality of latches that contain a plurality of exponents of operands for the operation;

a carry-save adder, coupled to the latches, that receives the exponents of operands and performs a carry-save add operation on the exponents of operands to produce a first result;

a control circuit for generating a control signal; and

a logic block, coupled to the carry-save adder, that receives the first result and performs a carry-lookahead add operation on the first result to produce a second result, the logic block having a logic circuit that performs an exclusive-OR logic operation between a most significant bit of the second result and the control signal to produce a value for use in the floating point multiply-accumulate operation,

whereby the apparatus forms the floating point multiply-accumulate operation using a single carry-save adder (CSA).